

3G Hotspot

Create your own 3G hotspot using portable DG-HR1160M (H/W Ver. B1) with any compatible 3G or EVDO dongle. You can quickly browse, send mail with multiple wireless devices connected to the router.

Power Bank

Simply charge this Power bank router from Wall Adapter or PC using the provided USB Cable until it is full, then simply charge your device whenever you need power. Its high-capacity, rechargeable 4400mAh battery pack increases energy efficiency and is ideal device for travelling and long flight. LED battery meter displays Battery power level.

Media Sharing

Share your movies, music, photos, and documents on the go with this Media sharing device and watch, listen, view or access them on almost any wireless device using third party app. You can connect external USB storage like Flash Drive or HDD to the router and access it wirelessly.

Portable Power Bank 3G Router

DG-HR1160M

(H/W Ver. B1)



DIGISOL DG-HR1160M (H/W Ver. B1) is a 150Mbps Wireless 3G portable power bank router. It has a compact design, perfect to carry and connect to Internet instantly. It can be used as a Power bank to charge your smart phones when on the move. The USB port on the router can be used for USB media sharing or 3G Internet connection using a 3G dongle. It uses the latest wireless IEEE802.11n technology to stream data at 150Mbps to its wireless clients. DG-HR1160M (H/W Ver. B1) is truly a Portable Power Bank Router with Compact Design, Internet Access, Media Sharing and Power Bank.

Product Features & Compliances

- 3G Router compatible with HSPA+/EVDO USB dongle*
- Supports WLAN network speed up to 150Mbps
- Robust WLAN security
- USB Media Sharing
- USB interface for charging Smart phones

DG-HR1160M

(H/W Ver. B1)

Technical Specifications

Hardware Interface

- One RJ-45 10/100Mbps WAN/LAN Port.
- One micro USB port for power charging the battery of router.
- One USB port for connecting 3G dongle or USB media sharing or charging Smart phones.
- One Reset Button for factory default setting recovery
- Power ON/OFF switch
- One Push button to check the battery status.
- Internal Antenna
- Status LED Indicator

Frequency band

- 2.400 – 2.4835GHz

WAN

- 3G
- Dynamic IP
- Static IP
- PPPoE

Advanced Features

- Port Forwarding
- DDNS
- Media Sharing

Battery

- Internal 4400mAh rechargeable battery, 5VDC/1.0A
- Operating Time: > 8hrs
- Standby Time: >10hrs

Environmental Specifications

- Operating temperature: -10°C ~ 55°C
- Storage temperature: -20°C ~ 60°C
- Storage humidity: 5 ~ 90% (Non-condensing)

Dimensions

- Net: 96(L)*46(W)*23(H)mm
- Gross: 170(L)*77(W)*45(H)mm

Weight

- Net Weight: 124 gms
- Gross Weight: 200 gms

Package contents

- DG-HR1160M (Portable Power Bank 3G Router)
- USB Cable
- Quick Installation Guide

Minimum system requirements

- Windows 98/Me/2000/XP/Vista/7/ 8
- Notebook or Desktop PC with wireless network Interface card.
- A web browser.



Ordering Information:

DG-HR1160M (H/W Ver. B1) : Portable Power Bank 3G Router

* Please refer 3G Dongle Compatibility List on Website for supported 3G Dongles.

** Power Adapter is not included in standard package.

DIGISOL, the DIGISOL Logo are trademarks and/or registered trademarks of Smartlink Network Systems Ltd. Other trademarks, product, service and company names mentioned are the property of their respective owners. Information is subject to change without notice. The actual product appearance may differ from the one shown here. © 2012 Smartlink Network Systems Ltd.

All rights reserved.